

ZERO ASSIGNMENT IN MULTIVARIABLE SYSTEM USING POLE ASSIGNMENT METHOD

Ye.M. Smagina

*Department of Chemical Engineering, Technion,
Haifa, Israel 32000
email: cermssy@tx.technion.ac.il*

Abstract

In the paper we consider the invariant zero assignment problem in a linear multi-variable system with several inputs/outputs by constructing a system output matrix. The problem is reduced to the pole assignment problem by a state feedback (modal control) in a descriptor system or a regular one. It is shown that the zero assignment and pole assignment are mathematically equivalent problems.

1 INTRODUCTION

For the first time the problem of the arbitrary zero assignment by choosing the output matrix was studied in (Rosenbrock, 1970, Theorem 4.1) and it is formulated briefly as follows: let an output matrix be arbitrarily chosen for a system. It is necessary to find this matrix so that the obtained system is observable and its transfer function matrix has the assigned numerators $\epsilon_i(s)$ of diagonal elements of Smith-McMillan form.

Rosenbrock showed that such the output matrix can always be chosen if the degrees of $\epsilon_i(s)$ satisfy some conditions. But these conditions are rather complicate for the designing. From this point of view we will consider the zero assignment method which assigns the zero polynomial $\psi(s) = \epsilon_1(s)\epsilon_2(s) \cdots \epsilon_r(s)$ entirely. Such a statement simplifies considerably Rosenbrock's conditions.

The problem of the zero polynomial assignment (zero assignment) has been studied in the works of the author. In the first works (Smagina,1984; Smagina,1986) the iterative zero assignment method was proposed, in the following works (Smagina,1985; Smagina,1991) the analytic zero assignment method was studied and it was discovered (Smagina, 1985) that the zero assignment problem is mathematically equivalent to the pole assignment problem. Later on the above result was formally proved using the special Yokoyama's canonical form (Smagina, 1996). A similar result has been obtained in (Syrmas and Lewis,1993) by using Hessenberg's canonical form.

In the present paper we prove the equivalence between the zero and pole assignment problems without using the complex canonical transformations. It is shown that, in general, the zero assignment is equivalent to the pole assignment in a descriptor system. When there is no restriction on an assigned zero polynomial degree then the zero assignment is equivalent to the pole assignment in a reduced regular dynamical system.

2 PROBLEM STATEMENT

We consider a linear multivariable dynamical system in the state-space

$$\dot{x} = Ax + Bu, \quad (1)$$

with the output

$$y = Hx \quad (2)$$

where x is a state n -vector, u is an input r -vector, y is an output l -vector ($r, l \leq n$); A, B, H are real constant matrices of the appropriate sizes. It is assumed that $\text{rank} B = r$, $\text{rank} H = l$.

It is known (MacFarlane and Karcianias, 1976) that finite invariant zeros of system (1), (2) are defined as the set of complex s which satisfies the rank equality

$$\text{rank} P(s) = \text{rank} \begin{bmatrix} sI - A & -B \\ H & O \end{bmatrix} < n + \min(r, l) \quad (3)$$

If $r = l$ then the finite invariant zeros are defined as zeros of the polynomial

$$\psi(s) = \det P(s) \quad (4)$$

Since there exist no invariant zeros in "almost all" system (1), (2) with $r \neq l$ (Davison and Wang, 1974) then we will consider the zero assignment problem for the "square" system (1),(2) with $r = l$.¹ Therefore, the zero assignment is formulated as follows.

Problem 1 *For the pair (A, B) find an output matrix H which ensures the coincidence of the polynomial $\psi(s)$ with a preassigned polynomial*

$$\psi_a(s) = \beta_0 + \beta_1 s + \dots + \beta_\mu s^\mu \quad (5)$$

where $\mu \leq n - r$.²

From the practical motivation it is necessary to impose the following condition on the matrix H :

$$i) \text{ the pair } (A, H) \text{ is observable.} \quad (6)$$

Remark 1 *It has been shown in the previous works of the author (Smagina, 1984; Smagina, 1986) that condition (6) is fulfilled if any zero $\bar{s}_i, i = 1, \dots, \mu$ of the preassigned polynomial $\psi_a(s)$ (5) does not coincide with any eigenvalue $\lambda_j(A), j = 1, \dots, n$ of the matrix A*

$$\bar{s}_i \neq \lambda_j(A), \quad i = 1, \dots, \mu, j = 1, \dots, n. \quad (7)$$

¹ If $r \neq l$ then it would be desirable to solve the zero assignment problem by "squaring down" system inputs or outputs.

²The maximum number of zeros in a n order system with r inputs/outputs is $n - r$ (Davison and Wang, 1974).

3 REDUCTION TO POLE ASSIGNMENT IN DESCRIPTOR SYSTEM

It follows from the condition $\text{rank} B = r$ that B has r linearly independent rows. At first for simplicity we consider the matrix B of the following structure

$$B = \begin{bmatrix} B_1 \\ B_2 \end{bmatrix} \quad (8)$$

where B_1 and B_2 are $(n-r) \times r$ and $r \times r$ blocks respectively, moreover,

$$\det B_2 \neq 0.$$

We introduce the $n \times n$ -nonsingular transformation matrix

$$N = \begin{bmatrix} I_{n-r} & -B_1 B_2^{-1} \\ O & I_r \end{bmatrix} \quad (9)$$

which reduces the matrix B to the form

$$NB = \begin{bmatrix} I_{n-r} & -B_1 B_2^{-1} \\ O & I_r \end{bmatrix} \begin{bmatrix} B_1 \\ B_2 \end{bmatrix} = \begin{bmatrix} O \\ B_2 \end{bmatrix}$$

and we transform the system matrix $P(s)$ into $\bar{P}(s)$ by means of the strict system equivalence operations (Pugh et al, 1987) which preserve the finite and infinite zeros of the elementary divisors of a regular matrix pencil:

$$\bar{P}(s) = \begin{bmatrix} N & O \\ O & I_l \end{bmatrix} P(s) \begin{bmatrix} N^{-1} & O \\ O & I_r \end{bmatrix} = \begin{bmatrix} sI - N A N^{-1} & -N B \\ H N^{-1} & O \end{bmatrix} \quad (10)$$

We decompose the matrices A and H as

$$A = \begin{bmatrix} A_{11} & A_{12} \\ A_{21} & A_{22} \end{bmatrix}, \quad H = \begin{bmatrix} H_1 & H_2 \end{bmatrix}$$

with the blocks $A_{11}, A_{12}, A_{21}, A_{22}, H_1, H_2$ having sizes $(n-r) \times (n-r)$, $(n-r) \times r$, $r \times (n-r)$, $r \times r$, $l \times (n-r)$, $l \times r$ respectively and calculate

$$N A N^{-1} = \begin{bmatrix} \bar{A}_{11} & \bar{A}_{12} \\ \bar{A}_{21} & \bar{A}_{22} \end{bmatrix}, \quad H N^{-1} = \begin{bmatrix} \bar{H}_1 & \bar{H}_2 \end{bmatrix}$$

where

$$\begin{aligned} \bar{A}_{11} &= A_{11} - B_1 B_2^{-1} A_{21}, \\ \bar{A}_{12} &= (A_{11} - B_1 B_2^{-1} A_{21}) B_1 B_2^{-1} + A_{12} - B_1 B_2^{-1} A_{22}, \\ \bar{A}_{21} &= A_{21}, \quad \bar{A}_{22} = A_{21} B_1 B_2^{-1} + A_{22}, \\ \bar{H}_1 &= H_1, \quad \bar{H}_2 = H_2 B_1 B_2^{-1} + H_2 \end{aligned} \quad (11)$$

Using (11), we represent $\bar{P}(s)$ as follows

$$\bar{P}(s) = \begin{bmatrix} sI_{n-r} - \bar{A}_{11} & -\bar{A}_{12} & O \\ -\bar{A}_{21} & sI_r - \bar{A}_{22} & -B_2 \\ \bar{H}_1 & \bar{H}_2 & O \end{bmatrix} \quad (12)$$

The finite and infinite zeros (Verghese et al.,1981) of $P(s)$ and $\bar{P}(s)$ coincide because the strict system equivalence operations preserve the finite and infinite elementary divisors of the regular pencil. Hence, the finite zeros of the system (1),(2) with $r = l$ coincide with zeros of the polynomial $\det \bar{P}(s)$:

$$\psi(s) = \det P(s) = \det \bar{P}(s). \quad (13)$$

Using the block structure of $\bar{P}(s)$, we calculate

$$\det \bar{P}(s) = (-1)^q \det B_2 \det \begin{bmatrix} sI_{n-r} - \bar{A}_{11} & -\bar{A}_{12} \\ \bar{H}_1 & \bar{H}_2 \end{bmatrix} \quad (14)$$

where an integer $q > 0$.

As a result *Problem 1* is reformulated as follows.

Problem 2 Find matrices $\bar{H}_1$ and $\bar{H}_2$ such that the following equality could take place

$$\det \begin{bmatrix} sI_{n-r} - \bar{A}_{11} & -\bar{A}_{12} \\ \bar{H}_1 & \bar{H}_2 \end{bmatrix} = \psi_a(s) \quad (15)$$

Condition (6) will be guaranteed by (7).

If $\bar{H}_1$ and $\bar{H}_2$ are found, the original output matrix $H = \begin{bmatrix} H_1 & H_2 \end{bmatrix}$ of system (1),(2) is defined as follows

$$H = \begin{bmatrix} H_1 & H_2 \end{bmatrix} = \begin{bmatrix} \bar{H}_1 & \bar{H}_2 \end{bmatrix} N = \begin{bmatrix} \bar{H}_1 & -\bar{H}_1 B_1 B_2^{-1} + \bar{H}_2 \end{bmatrix}.$$

Therefore,

$$H_1 = \bar{H}_1, \quad H_2 = \bar{H}_2 - \bar{H}_1 B_1 B_2^{-1}. \quad (16)$$

Now we will show that *Problem 2* is equivalent to a pole assignment problem in a descriptor system formed from the blocks of the matrix in (15).

Denote

$$E = \begin{bmatrix} I_{n-r} & O \\ O & O \end{bmatrix}, \quad F = \begin{bmatrix} \bar{A}_{11} & \bar{A}_{12} \\ O & O \end{bmatrix}, \quad G = \begin{bmatrix} O \\ -I_r \end{bmatrix},$$

$$K = \begin{bmatrix} \bar{H}_1 & \bar{H}_2 \end{bmatrix} \quad (17)$$

Theorem 1 The zero assignment problem in system (1),(2) with $\text{rank} B = r$ is equivalent to the pole assignment problem in the following descriptor system

$$E\dot{w} = Fw + Gv \quad (18)$$

by using the feedback proportional state regulator

$$v = Kw \quad (19)$$

with the $r \times n$ matrix K .

Therefore, the matrix K obtained will guarantee the condition

$$\det(sE - F - GK) = \psi_a(s) \quad (20)$$

In (18) w is a state n vector, v is an input r vector.

Proof. The proof follows directly from (4), (13), (15) and notations (17) i.e.

$$\det P(s) = \det \bar{P} = \det \begin{bmatrix} sI_{n-r} - \bar{A}_{11} & -\bar{A}_{12} \\ \bar{H}_1 & \bar{H}_2 \end{bmatrix} = \det(sI - F + GK) \quad \text{Q.E.D.}$$

In the remaining part of this section we consider the matrix B having an arbitrary structure. By applying the state transformation $\bar{x} = Mx$ ³ which rearranges the rows of B in (1) we bring the matrix B to the form

$$MB = \begin{bmatrix} \tilde{B}_1 \\ \tilde{B}_2 \end{bmatrix} \quad (21)$$

with $\text{rank} \tilde{B}_2 = r$. Then we consider the transformation matrix which has structure (9) and brings the matrix $P(s)$ to $\bar{P}(s)$ by strict system equivalence transformations (10) with N replaced by

$$\bar{N} = NM. \quad (22)$$

Further, we can use the above approach with $\bar{H} = [\bar{H}_1, \bar{H}_2] = H\bar{N}^{-1}$. Then from the relation $H = \bar{H}NM$ we can calculate the matrix H as follows

$$H = [\bar{H}_1, \bar{H}_2] \begin{bmatrix} I_{n-r} & -\tilde{B}_1\tilde{B}_2^{-1} \\ O & I_r \end{bmatrix} M = [\bar{H}_1, \bar{H}_2 - \bar{H}_1\tilde{B}_1\tilde{B}_2^{-1}] M \quad (23)$$

Therefore, we have shown that the zero assignment problem in system (1), (2) is reduced to the pole assignment problem in the descriptor system (18) of order n with r inputs. Recently a number of authors (Armantano, 1984; Chu, 1988; Blanchini, 1990; etc.) has considered the pole assignment problem by the proportional state feedback in a descriptor system of the general structure. The pole assignment solvability conditions are simplified in system (18) in virtue of the special structure of the matrices E, F, G . Further we will analyse the solvability conditions in detail and reveal their connection with the structure of original system (1), (2).

4 ANALYSIS OF POLE ASSIGNMENT SOLVABILITY CONDITIONS IN DESCRIPTOR SYSTEM

The pole assignment in descriptor system (18) may be formulated as follows:

Find a state feedback control law (19) so that

i) the closed loop pencil $F_c(s) = sE - (F + GK)$ is regular: $\det F_c(s) \neq 0$ (Gantmacher, 1959);

ii) the regular pencil $F_c(s)$ has $\mu \leq n - r$ preassigned (finite) eigenvalues.

We use the definition and the theorem of the regularizability from (Ozcaldizan and Lewis, 1990) in order to analyse the point i). System (18) is said to be regularizable by a proportional state feedback if the pencil $(sE - (F + GK))$ is regular for some matrix K . System (18) is always regularizable if and only if

$$\dim(E\mathcal{V}^* + \text{Im}G) = \dim\mathcal{V}^* \quad (24)$$

where $\mathcal{V}^*$ is a supremal element of the (F, E, G) -invariant subspace $\mathcal{V} : F\mathcal{V} \in E\mathcal{V} + \text{Im}G$ where $\text{Im}G$ is the image of G . It is clear that relation (24) holds for system (18) in virtue

³ M is a permutation $n \times n$ matrix which has a single unity element in each row(column) and zeros otherwise.

of the special structure of E, F, G (17). Therefore, the condition i) is always satisfied for system (18).

Then we analyse the point ii). As it is known the regular pencil $F_c(s)$ has $q = \text{rank} E$ eigenvalues (finite and infinite). It follows from the works (Cobb,1981; Verghese et al,1981; Yip and Sincovec,1981) that only controllable finite and infinite eigenvalues may be arbitrarily assigned. The finite eigenvalues of $F_c(s)$ are controllable if and only if

$$\text{rank}(sE - (F + GK), G) = n.$$

Since $\text{rank}(sE - (F + GK), G) = \text{rank}(sE - F, G)$ then we have the following controllability condition of the finite eigenvalues of $F_c(s)$

$$\text{rank}(sE - F, G) = n. \quad (25)$$

The infinite eigenvalues of $F_c(s)$ are controllable and may be shifted to preassigned points of the complex plan if the following condition takes place (Armantano, 1984; Blanchini,1990)

$$\text{rank}(E, G) = n.^4 \quad (26)$$

Therefore, condition (25) and (4) guarantee that a proportional feedback $r \times n$ matrix K exists so that the pole assignment problem has a solution.

It is evident that condition (4) is always fulfilled if $\text{rank} B = r$ by virtue of the special structure of E and G . The analysis of (25) gives

Assertion 1 *The finite eigenvalues of the pencil $F_c(s)$ are controllable if and only if the pair (A, B) is controllable,*

Proof. The proof follows from the rank equalities:

$$\begin{aligned} n &= \text{rank} [sI - A, B] = \text{rank} \left(\begin{bmatrix} \bar{N} & O \\ O & I \end{bmatrix} [sI - A, B] \bar{N}^{-1} \right) = \\ &= \text{rank} \begin{bmatrix} sI - \bar{A}_{11} & -\bar{A}_{12} & O \\ -\bar{A}_{21} & sI - \bar{A}_{22} & \bar{B}_2 \end{bmatrix} = \text{rank} [sI - \bar{A}_{11}, -\bar{A}_{12}] + r = \\ &\quad \text{rank} \begin{bmatrix} sI - \bar{A}_{11} & -\bar{A}_{12} & O \\ O & O & I_r \end{bmatrix} = \text{rank} [sE - F, G] \text{ Q.E.D.} \end{aligned}$$

Therefore, the solvability conditions of the pole assignment problem in descriptor system (18) are the controllability of the pair (A, B) and the rank fullness of B . Simultaneously these conditions are the solvability conditions of the zero assignment problem in system (1), (2). Taking into account *Remark 1* we have

Theorem 2 *If the pair (A, B) is controllable, $\text{rank} B = r$ and zeros $z_i, i = 1, \dots, \mu$ of a preassigned polynomial $\psi_a(s)$ don't coincide with eigenvalues of A , then there always exists the $r \times n$ matrix H which ensures that system (1), (2) is observable and has the preassigned zeros $z_i, i = 1, \dots, \mu, \mu \leq n - r$.*

Theorem 2 generalizes the appropriate results of the previous works of the author (Smagina, 1985; Smagina, 1996).

⁴ Condition: $\text{rank}[E, F\mathcal{S}_o, G] = n$ (Armantano, 1984) takes place if (4) is satisfied where $\mathcal{S}_o = \ker E$.

5 REDUCTION TO POLE ASSIGNMENT IN REGULAR STATE-SPACE SYSTEM

It is known (Kouvaritakis and MacFarlane, 1976) that the maximal number of finite invariant zeros in a n -order system with r inputs and outputs is equal to $n - r$. Using the method of sect. 4 we can arbitrarily assign any number $\mu \leq n - r$ of finite zeros (remaining $n - r - \mu$ zeros are situated in ∞). If there is no restriction on a number of finite zeros, namely, we can assign $\mu = n - r$ then *Problem 1* can be reduced to the pole assignment in a regular state-space system (regular pole-assignment problem). Indeed, the output $r \times n$ matrix H has rn elements, therefore, the matrix H has free variables which can be used in order to satisfy some supplementary requirements for the structure of the matrix H ensuring that system (1), (2) has exactly $n - r$ zeros. It is known (Smagina, 1990) that the following condition

$$\det HB \neq 0 \quad (27)$$

ensures that system (1), (2) possesses the maximal number of finite zeros. We transform system (1), (2) by means of the above nonsingular state transformation with the matrix $\bar{N} = NM$. The transformed output matrix has the form

$$\bar{H} = H\bar{N}^{-1} = [\bar{H}_1, \bar{H}_2] \quad (28)$$

with $r \times r$ block $\bar{H}_2$.

Assertion 2 $\det HB \neq 0$ if and only if

$$\det \bar{H}_2 \neq 0. \quad (29)$$

Proof. The following equalities take place

$$\det(HB) = \det(H\bar{N}^{-1}\bar{N}B) = \det\left([\bar{H}_1, \bar{H}_2] \begin{bmatrix} O \\ \tilde{B}_2 \end{bmatrix}\right) = \det(\bar{H}_2\tilde{B}_2)$$

Since $\tilde{B}_2$ is $r \times r$ nonsingular matrix, then $\det(\bar{H}_2\tilde{B}_2) \neq 0$ if and only if $\bar{H}_2$ is a nonsingular matrix. *Q.E.D.*

Restriction (29) will be used for the reduction of *Problem 1* to the regular pole assignment problem.

Theorem 3 *If we assign $\det \bar{H}_2 \neq 0$ then the zero assignment problem in (1), (2) is reduced to the pole assignment problem in the regular state-space system of order $n - r$ with r inputs*

$$\dot{\eta} = \bar{A}_{11}\eta - \bar{A}_{12}\bar{H}_2^{-1}\nu \quad (30)$$

by using the closed-loop proportional regulator

$$\nu = K\eta \quad (31)$$

where the $(n - r) \times (n - r)$ matrix $\bar{A}_{11}$ and $(n - r) \times r$ matrix $\bar{A}_{12}$ are defined from (11) with $B_i = \tilde{B}_i, i = 1, 2$; $r \times (n - r)$ matrix K coincides with the matrix $\bar{H}_1$.

Proof. If $\det \bar{H}_2 \neq 0$, then condition (27) takes place in (1), (2) in virtue of *Assertion 2*. Therefore, the polynomial $\psi_a(s)$ in (15) has the degree $\mu = n - r$. Using the determinant expansion formula (Gantmacher, 1959), we can calculate the determinant of the block matrix in (15) with $\det H_2 \neq 0$

$$\det \begin{bmatrix} sI_{n-r} - \bar{A}_{11} & -\bar{A}_{12} \\ \bar{H}_1 & \bar{H}_2 \end{bmatrix} = \det \bar{H}_2 \det(sI_{n-r} -$$

$$-\bar{A}_{11} + \bar{A}_{12}\bar{H}_2^{-1}\bar{H}_1 = \psi_a(s) \quad (32)$$

Since the matrix $\bar{H}_2$ does not depend on s , then we can change pole assignment condition (32) as follows

$$\det(sI_{n-r} - \bar{A}_{11} + \bar{A}_{12}\bar{H}_2^{-1}\bar{H}_1) = \psi_a(s).$$

Denoting $\bar{H}_1 = K$, we obtain the regular pole assignment problem. *Q.E.D.*

The necessary and sufficient solvability condition of the regular pole assignment problem in system (30) is the controllability of the pair $(\bar{A}_{11}, \bar{A}_{12}\bar{H}_2^{-1})$. We can express this condition in terms of system (1),(2).

Assertion 3 *If the pair (A, B) is controllable and $\text{rank} B = r$, then the pair $(\bar{A}_{11}, \bar{A}_{12}\bar{H}_2^{-1})$ is controllable.*

Proof. Let the pair (A, B) be controllable, then the rank equality: $\text{rank}(sI - A, B) = n$ takes place for any complex s . Using the strict equivalence transformations, we have series of rank equalities

$$\begin{aligned} n &= \text{rank}(sI - A, B) = \text{rank} \left(\begin{bmatrix} \bar{N} & O \\ O & I \end{bmatrix} [sI - A, B] \bar{N}^{-1} \right) = \\ &= \text{rank} \begin{bmatrix} sI - \bar{A}_{11} & -\bar{A}_{12} & O \\ -\bar{A}_{21} & sI - \bar{A}_{22} & \bar{B}_2 \end{bmatrix} = \text{rank}(sI - \bar{A}_{11}, -\bar{A}_{12}) + r = \\ &= \text{rank} \begin{pmatrix} sI - \bar{A}_{11} & -\bar{A}_{12} \end{pmatrix} \begin{bmatrix} I & O \\ O & \bar{H}_2^{-1} \end{bmatrix} + r = \text{rank}(sI - \bar{A}_{11}, -\bar{A}_{12}\bar{H}_2^{-1}) + r \end{aligned}$$

Hence, $\text{rank}(sI - \bar{A}_{11}, -\bar{A}_{12}\bar{H}_2^{-1}) = n - r$. *Q.E.D.*

Remark 2 *Assertion 3 gives the general solvability conditions of Problem 1 with $\mu = n - r$: the pair (A, B) is controllable and $\text{rank} B = r$. These conditions coincide with the appropriate conditions of Theorem 2.*

Remark 3 *It should be noted that the nonsingularity of the block $\bar{H}_2$ ensures the rank fullness of the matrix H because $r = \text{rank}[\bar{H}_1, \bar{H}_2] = \text{rank} H \bar{N}^{-1} = \text{rank} H$.*

Therefore, the present method guarantees the rank fullness of H in constructed system (1), (2) having $n - r$ preassigned zeros.

In conclusion, we write the general zero assignment algorithm.

1. Verify the controllability of (A, B) . If (A, B) is not controllable then *Problem 1* has no solution.
2. Assign a desirable polynomial $\psi_a(s)$ of order $\mu \leq n - r$ with zeros s_i satisfying *Remark 1*.
3. Calculate M and N (formula (9)) for $B_i = \tilde{B}_i, i = 1, 2$.
4. Calculate $\bar{A}_{11}$ and $\bar{A}_{12}$ (formula (11)) for $B_i = \tilde{B}_i, i = 1, 2$.
5. If $\mu < n - r$, then solve the pole assignment problem in descriptor system (18) otherwise assign the nonsingular block $\bar{H}_2$ and solve the regular pole assignment problem in system (30).
6. Calculate H from (16) or (23).

6 EXAMPLES

To illustrate the main results we consider system (1) with $n = 4$, $r = 2$ and

$$A = \begin{bmatrix} 2 & 1 & 0 & 0 \\ 0 & 1 & 0 & 1 \\ 0 & 2 & 0 & 0 \\ 1 & 1 & 0 & 0 \end{bmatrix}, \quad B = \begin{bmatrix} 1 & 0 \\ 0 & 0 \\ 0 & 1 \\ 0 & 1 \end{bmatrix}. \quad (33)$$

EXAMPLE 1. It is necessary to find 2×4 output matrix H which guarantees $\mu = 2$ finite zeros: $s_1 = -1$, $s_2 = -2$ in system (1), (2) with A , B from (33), i.e.

$$\psi_a(s) = s^2 + 3s + 2. \quad (34)$$

We can reduce the zero assignment to the pole assignment problem in a regular system because μ is equal to the maximal number of zeros in a system. Pair (33) is controllable, $\text{rank} B = 2$ and the eigenvalues of A don't coincide with the preassigned zeros, therefore, *Problem 1* has a solution. As the two last rows of the matrix B are linearly dependent, then we should rearrange the rows of B by the permutation matrix

$$M = \begin{bmatrix} 0 & 0 & 1 & 0 \\ 0 & 1 & 0 & 0 \\ 1 & 0 & 0 & 0 \\ 0 & 0 & 0 & 1 \end{bmatrix},$$

therefore,

$$MB = \begin{bmatrix} 0 & 1 \\ 0 & 0 \\ 1 & 0 \\ 0 & 1 \end{bmatrix}, \quad \tilde{B}_1 = \begin{bmatrix} 0 & 1 \\ 0 & 0 \end{bmatrix}, \quad \tilde{B}_2 = \begin{bmatrix} 1 & 0 \\ 0 & 1 \end{bmatrix}. \quad (35)$$

For calculating $\bar{N}A\bar{N}^{-1}$ we first find

$$MAM^T = \begin{bmatrix} 0 & 2 & 0 & 0 \\ 0 & 1 & 0 & 1 \\ 0 & 1 & 2 & 0 \\ 0 & 1 & 1 & 0 \end{bmatrix}.$$

Using the partition of the matrix $MAM^T = \begin{bmatrix} \bar{A}_{11}^* & \bar{A}_{12}^* \\ \bar{A}_{21}^* & \bar{A}_{22}^* \end{bmatrix}$ with

$$\bar{A}_{11}^* = \begin{bmatrix} 0 & 2 \\ 0 & 1 \end{bmatrix}, \bar{A}_{12}^* = \begin{bmatrix} 0 & 0 \\ 0 & 1 \end{bmatrix}, \bar{A}_{21}^* = \begin{bmatrix} 0 & 1 \\ 0 & 1 \end{bmatrix}, \bar{A}_{22}^* = \begin{bmatrix} 2 & 0 \\ 1 & 0 \end{bmatrix},$$

we calculate the blocks $\bar{A}_{11}$, $\bar{A}_{12}$ from formulas (11) with $A_{ij} = \bar{A}_{ij}^*$ and $B_i = \tilde{B}_i$, $i = 1, 2$ from (35)

$$\bar{A}_{11} = \bar{A}_{11}^* - \tilde{B}_1 \tilde{B}_2^{-1} \bar{A}_{21}^* = \begin{bmatrix} 0 & 1 \\ 0 & 1 \end{bmatrix},$$

$$\bar{A}_{12} = \bar{A}_{11}^* \tilde{B}_1 \tilde{B}_2^{-1} + \bar{A}_{12}^* - \tilde{B}_1 \tilde{B}_2^{-1} \bar{A}_{22}^* = \begin{bmatrix} -1 & 0 \\ 0 & 1 \end{bmatrix}$$

Assigning the 2×2 block $\bar{H}_2$ in the 2×4 matrix $\bar{H} = [\bar{H}_1, \bar{H}_2]$ as unity matrix, we arrive at the pole assignment problem in the system

$$\dot{\eta} = \begin{bmatrix} 0 & 1 \\ 0 & 1 \end{bmatrix} \eta - \begin{bmatrix} -1 & 0 \\ 0 & 1 \end{bmatrix} \nu \quad (36)$$

by the feedback state regulator

$$\nu = \begin{bmatrix} k_{11} & k_{12} \\ k_{21} & k_{22} \end{bmatrix} \eta. \quad (37)$$

This problem has a solution because system (36) is controllable. It is evident that the matrix K has free elements, therefore, a family of matrices $\mathcal{K}$ will satisfy a solution. We assign $k_{11} = 1$, $k_{12} = 0$ and calculate

$$K = \begin{bmatrix} 1 & 0 \\ 6 & 5 \end{bmatrix}.$$

Since $K = \bar{H}_1$ and $\bar{H}_2 = I_2$, then

$$\bar{H} = \begin{bmatrix} 1 & 0 & 1 & 0 \\ 6 & 5 & 0 & 1 \end{bmatrix}.$$

Using (23), we calculate

$$H = \bar{H}\bar{N} = \begin{bmatrix} 1 & 0 & 1 & -1 \\ 0 & 5 & 6 & -5 \end{bmatrix}.$$

The reliability of this result is verified by calculating $\det P(s)$ for A , B from (33) and above H .

EXAMPLE 2. It is desirable to design output (2) for system (1) with A and B from (33) so that constructed system has the one finite zero $s_1 = -1$. In this case $\mu = 1$, $\psi_a(s) = s + 1$. It follows from *Theorem 2* that the problem has a solution because (A, B) is controllable, $\text{rank} B = 2$ and $s_1 \neq \lambda_i(A)$.

By substituting the calculated matrices $\bar{A}_{11}$, $\bar{A}_{12}$ from *Example 1* in (17) we construct the descriptor system (18) of order 4 with two inputs and

$$E = \begin{bmatrix} I_2 & O \\ O & O \end{bmatrix}, F = \begin{bmatrix} \bar{A}_{11} & \bar{A}_{12} \\ O & O \end{bmatrix}, G = \begin{bmatrix} O \\ -I_2 \end{bmatrix}.$$

It is necessary to shift one finite pole ⁵ of this system to -1 by proportional regulator(19) with $K = \begin{bmatrix} k_{11} & k_{12} & k_{13} & k_{14} \\ k_{21} & k_{22} & k_{23} & k_{24} \end{bmatrix}$. We can calculate some K from the family of matrices $\mathcal{K}$ satisfying condition (20) with the abovementioned E , F , G

$$K = \begin{bmatrix} 0 & 2 & 0 & 1 \\ 1 & 0 & 0 & 0 \end{bmatrix}$$

Since $K = \bar{H}$ then we find the matrix H using formula (23)

$$H = \begin{bmatrix} 0 & 2 & 0 & 1 \\ 0 & 0 & 1 & -1 \end{bmatrix}.$$

The calculation of $P(s)$ confirms the correctness of the solution.

⁵A second pole of the closed-loop system is situated in ∞ .

7 CONCLUSION

We have presented the original method which reduces the zero assignment problem to the pole assignment in a singular or regular dynamical systems. The equivalence between the zero and the pole assignment problems is proved. The solvability condition of the zero assignment problem in terms of the pair (A, B) is obtained.

References

- [1] V.A. Armentano. Eigenvalue placement for generalized linear systems. *System and Control letters*, **4**,199–202, 1984.
- [2] F. Blanchini. Controllability analysis and eigenvalue assignment for generalized state-space systems. *System and Control letters*, **15**,285–293, 1990.
- [3] K.W.E. Chu. Controllability condensed form and a state feedback pole assignment algorithm for descriptor systems. *IEEE Trans. Autom.Control*, **AC-33**,366–370, 1988.
- [4] D.J. Cobb. Feedback and pole assignment in descriptor variable systems. *Int.J.Control*, **33**,1135–1146, 1981.
- [5] E.J. Davison and S. Wang. Property and calculation of transmission zeros of linear multivariable systems. *Automatica*, **10**,643–658, 1974.
- [6] F.R. Gantmacher. *Theory of matrices*. Chelsea Publishing Co., New York, 1959.
- [7] A.G.J. MacFarlane and N. Karcanias. Poles and zeros of linear multivariable systems: a survey of the algebraic, geometric and complex variable theory. *Int.J.Control*, **24**,33–74, 1976.
- [8] K. Ozcaldiran and F.L. Lewis. Regularizability for singular system. *IEEE Trans. Autom.Control*, **AC-35**,1156–1160, 1990.
- [9] A.C. Pugh, G.E. Hayton, and P. Fretwell. Transformation of matrix pencil and implication in linear system theory. *Int.J.Control*, **45**,529–548, 1987.
- [10] H.H. Rosenbrock. *State-space and multivariable theory*. Nelson, London, 1970.
- [11] Ye.M. Smagina. Design of multivariable system with assign zeros. *Dep.in All-Union Inst. of Sci. and Techn. Inf., Moscow*,, **No.8309-84**,1–15, 1984.
- [12] Ye.M. Smagina. Security of specified zeros of multivariable system. In A.S.Vostrikov, editor, *Automatic control of objects with varying characteristics*, pages 145–151. NETI, Novosibirsk,Russia, 1986.
- [13] Ye.M. Smagina. Computing and specification of zeros in a linear multi-dimension systems. *Avtomatika i telemekhanika*, **12**,165–173, 1987.
- [14] Ye.M. Smagina. A method of designing of observable output ensuring given zero location. *Problems of Control and Information Theory*, **20**,299–307, 1991.
- [15] Ye.M. Smagina. The relationship between the transmission zero assignment problem a modal control method. *Journal of Computer and System Science Intern.*, **35**,39– 1996.

- [16] V.L. Syrmos and F.L. Lewis. Transmission zero assignment using semistate description. *IEEE Trans. Autom. Control*, **AC-38**,1115–1120, 1993.
- [17] G.C. Verhese, B.C. Levy, and T. Kailath. A generalised state-space for singular systems. *IEEE Trans. Autom. Control*, **AC-26**,811–831, 1981.
- [18] E.L. Yip and R.F. Sincovec. Solvability, controllability and observability of continuous descriptor systems. *IEEE Trans. Autom. Control*, **AC-26**,702–707, 1981.